

|                              |  |
|------------------------------|--|
| <b>OS</b>                    | Linux  |
| <b>BNC Video Input</b>       | 1-CH   |
| <b>Input BNC Camera</b>      | HD 4K to 1080P TVI / CVI / AHD Coax Analog Camera  |
| <b>POS</b>                   | GILBARCO Passport, Verifone Ruby2 Topaz, JMISC, SAM4S, 7 Eleven, CASIO, LOC, pcAmerica, Keystroke, StoreTender, POSitouch, AST, L-BOSS, MicroSoft Dynamic, MODISoft, NRS, Focus etc. |
| <b>Input Resolution</b>      | 8MP/6MP/5MP/4MP/3MP/1080p  |
| <b>IP Video Output</b>       | 1-CH   |
| <b>Output Video Standard</b> | NTSC   |
| <b>Plug and Play</b>         | Yes  |
| <b>Number of Rows</b>        | 1-48 Rows  |
| <b>Number of Column</b>      | 1-120 Columns  |
| <b>Character Color</b>       | Red, Yellow, Orange, Blue, Black, White  |
| <b>Character Font Size</b>   | 4 Levels   |
| <b>Line Processing</b>       | Compress, Justification, Scroll Delay  |
| <b>Auto Scrolling</b>        | Yes  |
| <b>Overlay Area Size</b>     | Adjustable   |
| <b>Overlay Area</b>          | Adjustable   |
| <b>RS232</b>                 | Yes  |
| <b>Network Port</b>          | 1 x RJ-45 10/100M TCP/IP/UDP   |
| <b>USB Port</b>              | 2xUSB2.0   |
| <b>Exceptions</b>            | VOID, Cancel, No Sale, Discount, Coupon, Return, Delete, Price Change, or Customized define.   |
| <b>Exception Operator</b>    | >, <, >=, <=   |
| <b>Alert</b>                 | Email, Buzzer, Phone Notification, Color Switch  |
| <b>XVR/NVR/CMS</b>           | Supports All ONVIF Compatible XVR/NVR/CMS  |
| <b>Input Power</b>           | DC 12V~2A  |
| <b>Operating Temperature</b> | 10" ~ 40" (50"~104")   |
| <b>Dimension</b>             | 7" x 5" x 2"   |
| <b>Weight</b>                | ≤ 3lb  |



## PVTs-TAC-1 POS Text Inserter for HD Analog Cameras and DVR, CVI, TVI, AHD