

Chime ED-R1



Overview

The ED-R1 is a wireless chime mainly used with ED-525B-WB dual-lens video doorbells.

Features


- Simple installation, plug and play.
- 5-level volume adjustment, 3 ringtones available.
- Supports connection to doorbell through Sub-1 GHz.

Specifications

Model	ED-R1
Chime	
Connection method	Sub-1 GHz
Speaker	Built-in speaker
General	
Dimensions	53.6 mm × 85.6 mm × 39.8 mm
Weight	Net weight: 80g Gross weight: 125g
Power consumption	3W
Installation method	Install the plug directly into the socket
Button	From left to right: volume adjustment, reset status, change ringtone
Power source	As per definitions by different countries/regions
Operating temperature	-20 °C to 50 °C

Compliance	
NDA Compliant	Support

Dimensions



Zhejiang Uniview Technologies Co., Ltd.

- <http://www.uniview.com>
- overseasbusiness@uniview.com; globalsupport@uniview.com
- No. 369, Xietong Road, Xixing Sub-district, Binjiang District, Hangzhou City, 310051, Zhejiang Province, China



©2023-2025 Zhejiang Uniview Technologies Co., Ltd. All rights reserved.
*Product specifications and availability are subject to change without notice.
*Despite our best efforts, technical or typographical errors may exist in this document.
Uniview cannot be held responsible for any such errors and reserves the right to change the contents of this document without prior notice.